



PeakTech® 6085
0 - 15 V DC / 0 - 2 A DC Analog



PeakTech® 6080
0 - 15 V DC / 0 - 3 A DC digital



Diese beiden Netzgeräte im modernen Design wurden speziell für den Service- und Ausbildungssektor konzipiert und die beleuchteten 16 mm LCD-Anzeigen bzw. die Analoganzeigen ermöglichen eine schnelle und präzise Ablesung der eingestellten Werte. Die Ausgangsspannung bzw. der Ausgangsstrom ist kontinuierlich veränderbar.

- Überlastschutz und kurzschlussfest
- 16 mm LCD-Anzeigen mit Hintergrundbeleuchtung (P 6080)
- Analoge Messwerke für Spannung und Strom (P 6085)
- Lüfterfreies Gehäusedesign
- 4 mm Sicherheitsbuchsen
- Sicherheit: EN 61010-1
- Zubehör: Netzkabel und Bedienungsanleitung



These power supplies in modern design are constructed especially for the service centers and education fields. The 16 mm LCD with backlight or analogue displays allow the user to read the fixed values very fast, precise and the outputs for constant voltage and current are continuously adjustable.

- Short-circuit and overload protected
- 16 mm LCD with backlight (P 6080)
- Analogue moving coil voltage and current display (P 6085)
- Fan-free case design
- 4 mm safety jacks
- Safety: EN 61010-1
- Accessories: Power cable and Manual

► SPECIFICATIONS	P 6080	P 6085
Ausgangsspannung / Output voltage	0 - 15 V DC	0 - 15 V DC
Ausgangsstrom / Output current	0 - 3 A DC	0 - 2 A DC
Ausgangsleistung / Output power	45 W	30 W
Restwelligkeit / Residual ripple (U)	0,5 mV eff/rms	1 mV eff/rms
Restwelligkeit / Residual ripple (I)	3 mA eff/rms	6 mA eff/rms
Betriebsspannung / Operation voltage	115/230 V AC; 50/60 Hz	115/230 V AC; 50/60 Hz
Abmessungen / Dimensions (BxHxT/WxHxD)	95 x 160 x 225 mm	95 x 160 x 225 mm
Gewicht / Weight	2 kg	2 kg