

## PeakTech® 1030 PROD-ID: P 1030

[BACK](#)

### AC Voltage Detector 90 - 1000 V AC

Easy to use, for non-contact detection of AC voltage from 90 V to 1000 V. Suitable for outlets, lamp sockets or against wire insulation testing. Suitable for conductor tracking of flush-mounted cables and localisation of line interruptions. If AC-voltage is at the measuring point, it is visually indicated by a flashing red LED and the integrated buzzer sounds. The probe lights green when the measuring point is free of voltage.

- With acoustic and visual signal if voltage is found at the measuring point
- Power ON/OFF switchable
- Suitable for circuits of 50/60 Hz
- Rugged double mold case convient size with pocket clip fit in shirt pocket
- All outer surfaces are non-conductive for safety
- Build in flashlight with ON/OFF-button
- Safety: EN 61010-1; CAT III 1000 V
- Accessories: batteries and manual



#### MANUAL

[PeakTech 1030 11-2018F.pdf \(286.4 kB\)](#)

#### PICTURES

[1030 Front.jpg \(101.8 kB\)](#)

[1030 L.jpg \(115.6 kB\)](#)

[1030 R.jpg \(121.4 kB\)](#)

Operation range	90 ~ 1000 V AC; 50/60 Hz
Operation temperature	-10 ... +50 °C
Operation voltage	2 x 1,5 V AAA (UM-4) batteries
Dimensions (WxH)	157 x 26 mm
Weight	50 g
EAN-13	4250569400087

